



FlexDevice-L

www.star-cooperation.com

BENEFITS

- ARM Cortex A9 dual core (800 MHz) with 1 GByte DDR3 RAM
- 10 bus channels (via pluggable transceivers)
- Up to 7 Ethernet channels
- Up to 10 CAN channels
- Up to 8 FlexRay channels (4 channel A and 4 channel B)
- Wi-Fi and Bluetooth extension available
- Wake-up/sleep mode support
- Startup <200ms possible
- IP67
- Temperature range -40°C to +85°C

FLEXDEVICE-L – THE MULTIFUNCTIONAL BUS CONTROL UNIT

FlexDevice-L is the flagship of the FlexDevice product range, which is used and recognized by many car manufacturers and component suppliers in their automotive electronics development. The FlexDevice family provides manifold solutions for

- gateways between different automotive bus systems,
- bus interfaces,
- remaining bus simulation,
- signal manipulation,
- data logging and
- rapid prototyping.

The multifunctional bus control unit FlexDevice-L supports the current and upcoming bus systems and has numerous variable interfaces, thus covering most of the application fields where bus interfaces are required. This device is appreciated by embedded software developers since it facilitates the implementation and testing of even very tricky gateway applications and prototyping functionalities.

Together with the comprehensive FlexDevice-L software family, the developers are enabled to set up and control their bus systems and ECU environment in a smart way.

FlexDevice-L

TECHNICAL FEATURES

- Altera Cyclone V SOC (integrated ARM Cortex A9 Dual Core CPU)
- 1 GByte DDR3 RAM
- 5 bus connectors that can be allocated flexibly via pluggable transceivers
- 2 bus interfaces are available on each bus connector
- Up to 4 FlexRay controllers (4 Bosch E-Ray Cores)
- Up to 8 FlexRay channels (4 channel A and 4 channel B) available on the bus connectors
- In any case, 2 FlexRay cores can be connected internally (self-synchronization)
- Up to 10 CAN-HS bus interfaces
- Up to 10 CAN-FD bus interfaces
- Wake-up/sleep support (wake-up possible via FlexRay or CAN)
- Up to 7 100 Mbit/s Ethernet bus interfaces
- Up to 7 BroadR-Reach bus interfaces
- 1 Gbit/s Ethernet configuration interface
- Integrated 1 Gbit/s Ethernet switch
- Micro SD card slot
- 1 USB 2.0 interface
- 4 digital inputs or outputs (DIO)
- 5 analog or digital inputs (ADI)

SOFTWARE SUPPORT

- The device is supported by FlexConfig RBS starting with version 4.0.

HARDWARE

Electrical Characteristics

Supply voltage	8-42 VDC
Supply current (Sleep Mode)	<5 mA (@ 12 V)
Supply current (Operation Mode)	<600 mA (@ 12 V)

Environmental Conditions

Temperature	Operating/Storage: -40°C to +85°C
IP-Code	IP67
Relative Humidity	Operating/Storage: 0 % to 90 % rH, condensing

SCOPE OF DELIVERY

- FlexDevice-L
- Documentation

ORDER INFORMATION FLEXDEVICE-L

Product	Description	Order number
FlexDevice-L	The FlexDevice-L is a multifunctional autonomous bus system platform.	3-V0870A01

ORDER INFORMATION ACCESSORY PARTS

Product	Description	Order number
FlexConfig RBS runtime	Runtime license for RBS execution. Required once per device.	3-00700J01
FlexConfig Gateway runtime	Runtime license for gateway execution. Required once per device. (Requires "FlexConfig RBS runtime")	3-00701E01
FlexConfig Control runtime	Runtime license for signal manipulation. Required once per device. (Requires "FlexConfig RBS runtime")	3-00701G01
FlexConfig Analyzing runtime	Runtime license for analyzing bus data. Required once per device.	3-00701J01
FlexConfig Logging runtime	Runtime license for recording bus data. Required once per device.	3-00701001
FlexTiny3 1000BASE-T1	Pluggable transceiver module with two 1000BASE-T1 transceivers (88Q2112-A2-NYD2A000, Marvell)	3-00882H02
FlexTiny3 100BASE-T1	Pluggable transceiver module with two 100BASE-T1 transceivers (BCM89810A2AMLG, Broadcom)	3-00882C02
FlexTiny3 100BASE-T1 switch	Pluggable transceiver module with one 100BASE-T1 switch (BCM89500BQLEG, Broadcom)	3-00882D01
FlexTiny3 1000BASE-TX switch	Pluggable transceiver module with one 1000BASE-TX switch (88E6350RA1-TFJ21000, Marvell)	3-00882B01
FlexTiny3 FlexRay	Pluggable transceiver module with two FlexRay transceivers (TJA1081BTS, NXP)	3-00880A01
FlexTiny3 4x CAN-FD/HS	Pluggable transceiver module with four CAN-FD/HS transceivers (MCP2562FD, Micrel)	3-00881G02
FlexTiny3 2x CAN-FD/HS	Pluggable transceiver module with two CAN-FD/HS transceivers (TJA1145T/FD, NXP)	3-00881E01
FlexTiny3 4x LIN & 2x SENT	Pluggable transceiver module with four LIN (TJA1021T, NXP) and two SENT transceivers	3-00884A02
FlexTiny3 K-Line & UART & SPI	Pluggable transceiver module with one K-Line (TJA1021T, NXP), one UART and one SPI transceivers	3-00884B01
WiFi Extension	WiFi Extension for standard IEEE 802.11b/g/n	3-00870H02
Power cable (2 m)	2 pole Binder male to 2 banana male connector	3-00341D02
Gbit Ethernet bus cable (2 m)	8 Pole Binder male to RJ-45 connector	3-00342L01
Standard Binder bus cable (2 m)	8 pole Binder male to 9 pole D-Sub female connector	10016468
Standard Binder 2x Y-bus cable (2 m)	8 pole Binder male to 2 x 9 pole D-Sub female connector	10016469
Standard Binder 4x Y-bus cable (2 m)	8 pole Binder male to 4 x 9 pole D-Sub female connector	3-00342S01
BASE-T1 Binder bus cable (2 m)	8 pole Binder male to 9 pole D-Sub female connector - PIN 1,2 & 4,5	3-00342P01
BASE-T1 Binder 2x Y-bus cable (2 m)	8 pole Binder male to 2 x 9 pole D-Sub female connector - PIN 4,5	3-00342Q01
IO (DIO/ADI) cable (2 m)	7 pole Binder male to 9 pole D-Sub female connector	3-00341F02